C2257

12A581

Reversing lamp relay



FEMALE

Pin	Circuit	Circuit function
1	−	Reversing lamps relay, control
2	−	Ground
3	−	Voltage supplied at all times (overload protected)
4	−	not used
5	−	Reversing lamps relay, switched output

C2301

14A303

Upfitter relay #1



FEMALE

Pin	Circuit	Circuit function
30	1448 (OG/RD)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	153 (VT/YE)	Relay control circuit
87	1936 (OG/LG)	Voltage supplied when relay energized (overload protected)
87a	−	not used

C2300 (GY)

14A303

Upfitter switch



FEMALE

Pin	Circuit	Circuit function
1	156 (GY/OG)	Relay control circuit
2	19 (LB/RD)	Instrument illumination, feed
3	57 (BK)	Ground
4	−	not used
5	155 (GY/RD)	Relay control circuit
6	154 (VT/LG)	Relay control circuit
7	153 (VT/YE)	Relay control circuit
8	296 (WH/VT)	Voltage in Run (overload protected)

C2302

14A303

Upfitter relay #2



FEMALE

Pin	Circuit	Circuit function
30	1445 (RD/LG)	Voltage supplied at all times (overload protected)
85	57 (BK)	Ground
86	154 (VT/LG)	Relay control circuit
87	1933 (OG)	Voltage supplied when relay energized (overload protected)
87a	−	not used